

ZOOM X5v 5565 Modemlerde Port Açma

Modeminizin setupına girebilmek için Internet Tarayıcınıza (Internet Browser) (Internet Explorer veya Netscape) Modeminizin IP nosunu (not almıştınız, örnek http://10.0.0.2) yazıp, Enter basın.



Size Kullanıcı Adı (User Name) ve Şifre (Password) soracaktır. Değiştirmediyse default değerlerini modemizin kullanım klavuzundan (manuel) bulacağımız değerleri girin. Eğer kullanım klavuzunuz (manuel) yoksa Default değerleri ;

User Name : admin

Password : zoomadsl girin.

OK basın.



Çıkan menüde yukardan Advanced Setup seçin. Aşağıdaki Advanced Setup menüsü çıkacaktır. Bu menüde Virtual Server tıklayın.



Virtual Server Configuration menüsünde eD2K serverlerinin kullandığı TCP:4662 portunu yönlendirmek için aşağıdaki gibi doldurun. Host IP Address olarak PCnizin IP Nosunu girin (Not almıştınız, bu örnekte 10.0.0.10 kullanılmıştır).

Add This Settings tıklayın.

Zoom Configuration Manager - Microsoft Internet Explorer

File Edit View Favorites Tools Help

Address http://10.0.0.2/doc/index.htm

zoom

System Status ADSL Status Basic Setup Voice over IP Advanced Setup Help

Virtual Server Configuration

Virtual Server:
Configuring a Virtual Server can enable certain special applications, for example some Internet games or services (such as FTP) that require access to ports normally blocked by the firewall settings. More detailed information is available by clicking the Help icon.

Important: If you make changes to this page, you must click the **Save Changes** button and then the **Write Setting to Flash and Reboot** button. A **Confirm** page displays; click the button to complete the process. If not, any changes will be lost when you navigate to another page.

Public Port	Private Port	Port Type	Host IP Address	
6112	6112	TCP	10.0.0.10	Delete This Setting
6112	6112	UDP	10.0.0.10	Delete This Setting

- Use the following form to add special port that you want to be opened for your special application

Public Port	Private Port	Port Type	Host IP Address	
4662	4662	<input checked="" type="radio"/> TCP <input type="radio"/> UDP	10.0.0.10 PCnizin IP Nosu	Add This Setting

After you have saved your changes, you must write the new settings to flash and reboot. Click the button below to do this.

Write Settings to Flash and Reboot

The maximum number of entries above is 20. The maximum number of mapped ports is 20

Aynı şekilde KAD'ın kullandığı UDP:4672 portunu yönlendirmek için aşağıdaki gibi doldurun. Host IP Address olarak PCnizin IP Nosunu girin (Not almıştınız, bu örnekte 10.0.0.10 kullanılmıştır).

Add This Settings tıklayın. Yaptıklarınızı kayıt etmek için Write Settings to Flash and Reboot tıklayın. Modeminiz yaptıklarınızı kayıt ettikten sonra Reboot (kapanıp-açılacak) edecektir.

Zoom Configuration Manager - Microsoft Internet Explorer

Address: http://10.0.0.2/doc/index.htm

System Status | ADSL Status | Basic Setup | Voice over IP | Advanced Setup | Help

Virtual Server Configuration

Virtual Server:
Configuring a Virtual Server can enable certain special applications, for example some Internet games or services (such as FTP) that require access to ports normally blocked by the firewall settings. More detailed information is available by clicking the Help icon.

Important: If you make changes to this page, you must click the **Save Changes** button and then the **Write Setting to Flash and Reboot** button. A **Confirm** page displays; click the button to complete the process. If not, any changes will be lost when you navigate to another page.

Public Port	Private Port	Port Type	Host IP Address	
6112	6112	TCP	10.0.0.10	Delete This Setting
6112	6112	UDP	10.0.0.10	Delete This Setting

- Use the following form to add special port that you want to be opened for your special application

Public Port	Private Port	Port Type	Host IP Address	
4672	4672	<input type="radio"/> TCP <input checked="" type="radio"/> UDP	10.0.0.10 PCnizin IP nosu	Add This Setting

After you have saved your changes, you must write the new settings to flash and reboot. Click the button below to do this.

Write Settings to Flash and Reboot

The maximum number of entries above is 20. The maximum number of mapped ports is 20.